






中国认可
国际互认
检测
TESTING
CNAS L6791

Test Report issued under the responsibility of:



TEST REPORT IEC 62109-2 Safety of Power Converter for use in Photovoltaic Power Systems Part 2: Particular requirements for inverters	
Report Number.....	BL-SZ1930601-B01 attachment 1
Date of issue	Apr. 10, 2019
Total number of pages	25
Name of Testing Laboratory preparing the Report.....	Shenzhen BALUN Technology Co., Ltd
Applicant's name	Shenzhen SOFAR SOLAR Co., Ltd.
Address.....	401, Building 4, AnTongDa Industrial Park, District 68, XingDong Community, XinAn Street, BaoAn District, Shenzhen City, Guangdong Province, P.R. China
Test specification:	
Standard	IEC 62109-2:2011
Test procedure.....	Test report
Non-standard test method.....	N/A
Test Report Form No.....	IEC62109_2B
Test Report Form(s) Originator....	LCIE - Laboratoire Central des Industries Electriques
Master TRF	Dated 2016-11
Copyright © 2016 IEC System of Conformity Assessment Schemes for Electrotechnical Equipment and Components (IECEE System). All rights reserved.	
This publication may be reproduced in whole or in part for non-commercial purposes as long as the IECEE is acknowledged as copyright owner and source of the material. IECEE takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.	
If this Test Report Form is used by non-IECEE members, the IECEE/IEC logo and the reference to the CB Scheme procedure shall be removed.	
This report is not valid as a CB Test Report unless signed by an approved CB Testing Laboratory and appended to a CB Test Certificate issued by an NCB in accordance with IECEE 02.	



Test item description.....:	Solar Gird-tied Inverter	
Trade Mark.....:		
Manufacturer.....:	Same as the applicant	
Model/Type reference.....:	SOFAR 1100TL-G3, SOFAR 1600TL-G3, SOFAR 2200TL-G3, SOFAR 2700TL-G3, SOFAR 3000TL-G3, SOFAR 3300TL-G3	
Ratings.....:	See copy of marking label and model list.	
Responsible Testing Laboratory (as applicable), testing procedure and testing location(s):		
<input checked="" type="checkbox"/>	Testing Laboratory:	Shenzhen BALUN Technology Co., Ltd.
	Testing location/ address.....:	Block B, 1st FL, Baisha Science and Technology Park, Shahe Xi Road, Nanshan District, Shenzhen, Guangdong Province. P.R. China
	Tested by (name, function, signature).....:	Colin Chen 
	Approved by (name, function, signature)...:	Simon Qi 
<input type="checkbox"/>	Testing procedure: CTF Stage 1:	
	Testing location/ address.....:	
	Tested by (name, function, signature).....:	
	Approved by (name, function, signature)...:	
<input type="checkbox"/>	Testing procedure: CTF Stage 2:	
	Testing location/ address.....:	
	Tested by (name + signature).....:	
	Witnessed by (name, function, signature)..:	
	Approved by (name, function, signature)...:	
<input type="checkbox"/>	Testing procedure: CTF Stage 3:	
<input type="checkbox"/>	Testing procedure: CTF Stage 4:	
	Testing location/ address.....:	
	Tested by (name, function, signature).....:	
	Witnessed by (name, function, signature)..:	
	Approved by (name, function, signature)...:	
	Supervised by (name, function, signature) :	

List of Attachments (including a total number of pages in each attachment): See report BL-SZ1930601-B01.	
Summary of testing:	
Tests performed (name of test and test clause): 4.4.4.15.1 Fault-tolerance of residual current monitoring 4.4.4.15.2 Fault-tolerance of automatic disconnecting means 4.4.4.17 Cooling system failure – Blanketing test 4.8.2 Array insulation resistance detection for inverters for ungrounded and functionally grounded arrays 4.8.3 Array residual current detection 4.8.3.5 Protection by residual current monitoring Remark: - Other testing conditions considered in this test report, see General product information of the report BL-SZ1930601-B01 for details.	Testing location: See report BL-SZ1930601-B01.
Summary of compliance with National Differences (List of countries addressed): List of countries addressed: See report See report BL-SZ1930601-B01.	

Copy of marking plate:

The artwork below may be only a draft. The use of certification marks on a product must be authorized by the respective NCBS that own these marks.

		Solar Grid-tied Inverter
Model No.	SOFAR 3300TL-G3	
Max.DC Input Voltage	550V	
Operating MPPT Voltage Range	50~550V	
Max. Input Current	12A	
Max. PV Isc	15A	
Nominal Grid Voltage	L/N/PE,230Vac	
Max. Output Current	16A	
Nominal Grid Frequency	50/60Hz	
Max. Output Power	3300VA	
Power Factor	1(adjustable+/-0.8)	
Ingress protection	IP65	
Operating Temperature Range	-30~+60°C	
Topology	Non-isolated	
Protective Class	Class I	
Manufacturer:Shenzhen SOFARSOLAR Co., Ltd. Address: 401, Building 4, AnTongDa Industrial Park,District 68, XingDong Community, XinAn Street,BaoAn District, Shenzhen, China VDE0126-1-1,VDE-AR-N4105, IEC61727, IEC62116, UTE C15-712-1,AS4777		

Note:

1. The above markings are the minimum requirements required by the safety standard. For the final production samples, the additional markings which do not give rise to misunderstanding may be added.
 2. Label is attached on the side surface of enclosure and visible after installation
- Labels of other models are as the same with SOFAR 3300TL-G3's except the parameters of rating.

Test item particulars..... :	
Equipment mobility..... :	<input type="checkbox"/> movable <input type="checkbox"/> hand-held <input type="checkbox"/> stationary <input checked="" type="checkbox"/> fixed <input type="checkbox"/> transportable <input type="checkbox"/> for building-in
Connection to the mains..... :	<input type="checkbox"/> pluggable equipment <input type="checkbox"/> direct plug-in <input checked="" type="checkbox"/> permanent connection <input type="checkbox"/> for building-in
Enviromental category..... :	<input checked="" type="checkbox"/> outdoor <input type="checkbox"/> indoor unconditional <input type="checkbox"/> indoor conditional
Over voltage category Mains..... :	<input type="checkbox"/> OVC I <input type="checkbox"/> OVC II <input checked="" type="checkbox"/> OVC III <input type="checkbox"/> OVC IV
Over voltage category PV..... :	<input type="checkbox"/> OVC I <input checked="" type="checkbox"/> OVC II <input type="checkbox"/> OVC III <input type="checkbox"/> OVC IV
Mains supply tolerance (%)..... :	According to specified supply range
Tested for power systems..... :	TN
IT testing, phase-phase voltage (V)..... :	N/A
Class of equipment..... :	<input checked="" type="checkbox"/> Class I <input type="checkbox"/> Class II <input type="checkbox"/> Class III <input type="checkbox"/> Not classified
Mass of equipment (kg)..... :	See model list
Pollution degree..... :	PD3(Inside PD2)
IP protection class..... :	IP65
..... :	
Possible test case verdicts:	
- test case does not apply to the test object..... :	N/A
- test object does meet the requirement..... :	P (Pass)
- test object does not meet the requirement..... :	F (Fail)
Testing..... :	
Date of receipt of test item..... :	See report BL-SZ1930601-B01
Date (s) of performance of tests..... :	See report BL-SZ1930601-B01
.....	
General remarks:	
<p>"(See Enclosure #)" refers to additional information appended to the report. "(See appended table)" refers to a table appended to the report. The tests results presented in this report relate only to the object tested. This report shall not be reproduced except in full without the written approval of the testing laboratory. List of test equipment must be kept on file and available for review. Additional test data and/or information provided in the attachments to this report. Throughout this report a <input type="checkbox"/> comma / <input checked="" type="checkbox"/> point is used as the decimal separator.</p>	
Manufacturer's Declaration per sub-clause 4.2.5 of IEC60335-1:	
The application for obtaining a CB Test Certificate includes more than one factory location and a declaration from the Manufacturer stating that the sample(s) submitted for evaluation is (are) representative of the products from each factory has been provided..... :	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> Not applicable
When differences exist; they shall be identified in the General product information section.	

Name and address of factory (ies)..... :

See report BL-SZ1930601-B01

General product information:

See report BL-SZ1930601-B01

Throughout the test report following abbreviations may be used:

●	cl	clearance	●	int	internal distance
●	dcr	creepage distance	●	o-c	open-circuit
●	dti	distance through insulation	●	o-l	overload
●	PCE	Power Conversion Equipment	●	s-c	short-circuit
●	BI	basic insulation	●	SI	supplementary insulation
●	DI	double insulation	●	RI	reinforced insulation

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
4	GENERAL TESTING REQUIREMENTS		P
4.4.4	Single fault conditions to be applied		P
4.4.4.15	Fault-tolerance of protection for grid-interactive inverters		P
4.4.4.15.1	Fault-tolerance of residual current monitoring according to 4.8.3.5: the residual current monitoring system operates properly	See appended table 4.4.4.15.1	P
	a).. - The inverter ceases to operate		P
	- Indicates a fault in accordance with §13.9		P
	- Disconnect from the mains		P
	- not re-connect after any sequence of removing and reconnecting PV power		P
	- not re-connect after any sequence of removing and reconnecting AC power		P
	- not re-connect after any sequence of removing and reconnecting both PV and AC power		P
	b).. - The inverter continues to operate		P
	- the residual current monitoring system operates properly under single fault condition		P
	- Indicates a fault in accordance with §13.9		P
	c).. - The inverter continues to operate regardless of loss of residual current monitoring functionality		P
	- not re-connect after any sequence of removing and reconnecting PV power		P
	- not re-connect after any sequence of removing and reconnecting AC power		P
	- not re-connect after any sequence of removing and reconnecting both PV and AC power		P
	- Indicates a fault in accordance with §13.9		P
4.4.4.15.2	Fault-tolerance of automatic disconnecting means		P
4.4.4.15.2 .1	The means provided for automatic disconnection of a grid-interactive inverter from the mains shall:		P
	- disconnect all grounded current-carrying conductors from the mains		P
	- disconnect all ungrounded current-carrying conductors from the mains		P
	- be such that with a single fault applied to the disconnection means or to any other location in the inverter, at least basic insulation or simple separation is maintained between the PV array and the mains when the disconnecting means is intended to be in the open state.	See appended table 4.4.4.15.2 Fault-tolerance of automatic disconnecting	P
4.4.4.15.2 .2	Design of insulation or separation complies with requirements of 7.3.7 of Part 1: report here Part 1 comment and verdict.		P
4.4.4.15.2 .3	For non-isolated inverter, automatic checking of the isolation provided by a disconnect means after single fault.	See appended test table 4.4.4.15.2 Fault-tolerance of automatic disconnecting.	P
	If the check fail:		P
	- any still-functional disconnection means shall be left in the open position		P
	- at least basic or simple separation shall be maintained		P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	between the PV input and the mains		
	- the inverter shall not start operation		P
	- the inverter shall indicate a fault in accordance with 13.9		P
4.4.4.16	A stand-alone inverter with a transfer switch to transfer AC loads from the mains or other AC bypass source to the inverter output:	Grid-connected PV Inverter.	N/A
	- shall continue to operate normally		N/A
	- shall not present a risk of fire as the result of an out-of-phase transfer		N/A
	- shall not present a risk of shock as the result of an out-of-phase transfer		N/A
	- And having control preventing switching: components for malfunctioning		N/A
4.4.4.17	Cooling system failure – Blanketing test No hazards according to the criteria of sub-clause 4.4.3 of Part 1 shall result from blanketing the inverter This test is not required for inverters restricted to use only in closed electrical operating areas.	See appended test table Cooling system failure – Blanketing test.	P
	Test stop condition: time duration value or stabilized temperature		P
4.7	ELECTRICAL RATINGS TESTS		P
4.7.4	Stand-alone Inverter AC output voltage and frequency		N/A
4.7.4.1	General		N/A
4.7.4.2	Steady state output voltage at nominal DC input The steady-state AC output voltage shall not be less than 90 % or more than 110 % of the rated nominal voltage with the inverter supplied with its nominal value of DC input voltage.	See appended test table 4.7.4 Steady state Inverter AC output voltage and frequency	N/A
4.7.4.3	Steady state output voltage across the DC input range The steady-state AC output voltage shall not be less than 85 % or more than 110 % of the rated nominal voltage with the inverter supplied with any value within the rated range of DC input voltage.	See appended test table 4.7.4 Steady state Inverter AC output voltage and frequency	N/A
4.7.4.4	Load step response of the output voltage at nominal DC input The AC output voltage shall not be less than 85 % or more than 110 % of the rated nominal voltage for more than 1,5 s after application or removal of a resistive load.	See appended test table 4.7.4 Steady state Inverter AC output voltage and frequency	N/A
4.7.4.5	Steady state output frequency The steady-state AC output frequency shall not vary from the nominal value by more than +4 % or –6 %.	See appended test table 4.7.4 Steady state Inverter AC output voltage and frequency	N/A
4.7.5	Stand-alone inverter output voltage waveform		N/A
4.7.5.1	General		N/A
4.7.5.2	The AC output voltage waveform of a sinusoidal output stand-alone inverter shall have a total harmonic distortion (THD) not exceeding of 10 % and no individual harmonic at a level exceeding 6 %.		N/A
4.7.5.3	Non-sinusoidal output waveform requirements		N/A
4.7.5.3.1	General		N/A
4.7.5.3.2	The total harmonic distortion (THD) of the voltage		N/A

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	waveform shall not exceed 40 %.		
4.7.5.3.3	The slope of the rising and falling edges of the positive and negative half-cycles of the voltage waveform shall not exceed 10 V/ μ s measured between the points at which the waveform has a voltage of 10 % and 90 % of the peak voltage for that half-cycle.		N/A
4.7.5.3.4	The absolute value of the peak voltage of the positive and negative half-cycles of the waveform shall not exceed 1,414 times 110 % of the RMS value of the rated nominal AC output voltage.		N/A
4.7.5.4	Information requirements for non-sinusoidal waveforms The instructions provided with a stand-alone inverter not complying with 4.7.5.2 shall include the information in 5.3.2.6.		N/A
4.7.5.5	Output voltage waveform requirements for inverters for dedicated loads. For an inverter that is intended only for use with a known dedicated load, the following requirements may be used as an alternative to the waveform requirements in 4.7.5.2 to 4.7.5.3.		N/A
	The combination of the inverter and dedicated load shall be evaluated to ensure that the output waveform does not cause any hazards in the load equipment and inverter, or cause the load equipment to fail to comply with the applicable product safety standards.	See attached document: 4.7.5.5 Evaluation of inverter for dedicated load	N/A
	The inverter shall be marked with symbols 9 and 15 of Table C.1 of Part 1.		N/A
	The installation instructions provided with the inverter shall include the information in 5.3.2.13.		N/A
4.8	ADDITIONAL TESTS FOR GRID-INTERACTIVE INVERTERS		P
4.8.1	General requirements regarding inverter isolation and array grounding		N/A
	- Type of Array grounding supported		N/A
	- Inverter isolation		N/A
4.8.2	Array insulation resistance detection for inverters for ungrounded and functionally grounded arrays	(See attached table)	P
4.8.2.1	Array insulation resistance detection for inverters for ungrounded arrays	See below.	P
	Inverter shall have means to measure DC insulation resistance from PV input (array) to ground before starting operation		P
	Or Inverter shall be provided with instruction in accordance with 5.3.2.11.		P
	Measured DC insulation resistance:		P
	Inverter measurement circuit shall be capable of detecting insulation resistance below the limit value $R = V_{max}/30mA$ under normal conditions		P
	Inverter measurement circuit shall be capable of detecting insulation resistance below the limit value $R = V_{max}/30mA$ with ground fault in the PV array		P
	Isolated inverters shall indicate a fault if the insulation resistance is less than the limit value		P
	Isolated inverter fault indication maintained until insulation resistance has recovered to a value higher than the limit	Non-isolated inverter	N/A

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	value		
	Non-isolated inverters, or inverters with isolation not complying with the leakage current limits in the minimum inverter isolation requirements in Table 30:		P
	- shall indicate a fault in accordance with 13.9		P
	- shall not connect to the mains		P
4.8.2.2	Array insulation resistance detection for inverters for functionally grounded arrays	Inverters connected to ungrounded arrays.	N/A
	a-1)The value of the total resistance, including the intentional resistance for array functional grounding, the expected insulation resistance of the array to ground, and the resistance of any other networks connected to ground (for example measurement networks) must not be lower than $R = (V_{MAX PV}/30 \text{ mA})$ ohms.		N/A
	a-2) The installation instructions shall include the information required in 5.3.2.12.		N/A
	b-1) As an alternative to a), or if a resistor value lower than in a) is used, the inverter shall incorporate means to detect, during operation, if the total current through the resistor and any networks (for example measurement networks) in parallel with it, exceeds the residual current values and times in Table 31		N/A
	b-2) Inverter shall either disconnect the resistor or limit the current by other means		N/A
	b-3) If the inverter is a non-isolated inverter, or has isolation not complying with the leakage current limits in the minimum inverter isolation requirements in Table 30, it shall also disconnect from the mains.		N/A
	c) The inverter shall have means to measure the DC insulation resistance from the PV input to ground before starting operation, in accordance with 4.8.2.1.		N/A
4.8.3	Array residual current detection		P
4.8.3.1	General		P
4.8.3.2	30 mA touch current type test for isolated inverters	See appended table 4.8.3.2 30mA touch current type test for isolated inverters	P
4.8.3.3	Fire hazard residual current type test for isolated inverters	See appended table 4.8.3.3 Fire hazard residual current type test for isolated inverters	P
4.8.3.4	Protection by application of RCD's	Not used.	N/A
	- The requirement for additional protection in 4.8.3.1 can be met by provision of an RCD with a residual current setting of 30 mA, located between the inverter and the mains..		N/A
	- The selection of the RCD type to ensure compatibility with the inverter must be made according to rules for RCD selection in Part 1.		N/A
	- The RCD provided integral to the inverter, or		N/A
	- The RCD provided by the installer if details of the rating, type, and location for the RCD are given in the installation instructions per 5.3.2.9.		N/A
4.8.3.5	Protection by residual current monitoring	RCMU used for monitoring the residual current.	P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
4.8.3.5.1	General		P
	Where required by Table 30, the inverter shall provide residual current monitoring that functions whenever the inverter is connected to the mains with the automatic disconnection means closed.		P
	The residual current monitoring means shall measure the total (both a.c. and d.c. components) RMS current.		P
	As indicated in Table 30 for different inverter types, array types, and inverter isolation levels, detection may be required for excessive continuous residual current, excessive sudden changes in residual current, or both, according to the following limits:		P
	a) Continuous residual current: The inverter shall disconnect within 0,3 s and indicate a fault in accordance with 13.9 if the continuous residual current exceeds:		P
	- maximum 300 mA for inverters with continuous output power rating ≤ 30 kVA;	3.3K	P
	- maximum 10 mA per kVA of rated continuous output power for inverters with continuous output power rating > 30 kVA.		N/A
	The inverter may attempt to re-connect if the array insulation resistance meets the limit in 4.8.2.		P
	b) Sudden changes in residual current: The inverter shall disconnect from the mains within the time specified in Table 31		P
	The inverter indicates a fault in accordance with 13.9, if a sudden increase in the RMS residual current is detected exceeding the value in the table.		P
	The inverter may attempt to re-connect if the array insulation resistance meets the limit in 4.8.2.		P
4.8.3.5.2	Test for detection of excessive continuous residual current: test repeated 5 times and time to disconnect shall not exceed 0,3 s.	See appended test table 4.8.3.5.2 Test for detection of excessive continuous residual current	P
4.8.3.5.3	Test for detection of sudden changes in residual current repeated 5 times and each of the 5 results shall not exceed the time limit indicated in for each row (30mA, 60mA and 150mA) of Table 31.		P
4.8.3.6	Systems located in closed electrical operating areas	Not specified to be located in closed electrical operating area.	N/A
	The protection against shock hazard is not required if the installation information provided with the inverter indicates the restriction for use in a closed electrical operating area, and		N/A
	Installation information indicates what forms of shock hazard protection are and are not provided integral to the inverter, in accordance with 5.3.2.7.		N/A
	The inverter shall be marked as in 5.2.2.6.		N/A
5	MARKING AND DOCUMENTATION		P
5.1	Marking		P
5.1.4	Equipment ratings		P
	PV input ratings:		P
	- Vmax PV (absolute maximum) (d.c. V)		P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	- Isc PV (absolute maximum) (d.c. A)		P
	a.c. output ratings:		P
	- Voltage (nominal or range) (a.c. V)		P
	- Current (maximum continuous) (a.c. A)		P
	- Frequency (nominal or range) (Hz)		P
	- Power (maximum continuous) (W or VA)		P
	- Power factor range		P
	a.c input ratings:		N/A
	- Voltage (nominal or range) (a.c. V)		N/A
	- Current (maximum continuous) (a.c. A)		N/A
	- Frequency (nominal or range) (Hz)		N/A
	d.c. output ratings:		N/A
	- Voltage (nominal or range) (d.c. V)		N/A
	- Current (maximum continuous) (d.c. A)		N/A
	Protective class (I or II or III)		P
	Ingress protection (IP) rating per part 1		P
	An inverter that is adjustable for more than one nominal output voltage shall be marked to indicate the particular voltage for which it is set when shipped from the factory.		N/A
5.2	Warning markings		P
5.2.2	Content for warning markings		P
5.2.2.6	Inverters for closed electrical operating areas		P
	Where required by 4.8.3.6, an inverter not provided with full protection against shock hazard on the PV array shall be marked with a warning that the inverter is only for use in a closed electrical operating area, and referring to the installation instructions.		P
5.3	Documentation		P
5.3.2	Information related to installation		P
5.3.2.1	Ratings. Subclause 5.3.2 of Part 1 requires the documentation to include ratings information for each input and output. For inverters this information shall be as in Table 33 below. Only those ratings that are applicable based on the type of inverter are required.		P
	PV input quantities :		P
	- Vmax PV (absolute maximum) (d.c. V)		P
	- PV input operating voltage range (d.c. V)		P
	- Maximum operating PV input current (d.c. A)		P
	- Isc PV (absolute maximum) (d.c. A)		P
	- Isc PV (absolute maximum) (d.c. A)		P
	- Max. inverter backfeed current to the array (a.c. or d.c. A)		P
	a.c. output quantities:		P
	- Voltage (nominal or range) (a.c. V)		P
	- Current (maximum continuous) (a.c. A)		P
	- Current (inrush) (a.c. A, peak and duration)		P
	- Frequency (nominal or range) (Hz)		P
	- Power (maximum continuous) (W or VA)		P
	- Power factor range		P
	- Maximum output fault current (a.c. A, peak and duration or RMS)		P
	- Maximum output overcurrent protection (a.c. A)		P
	a.c. input quantities:		N/A

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	- Voltage (nominal or range) (a.c. V)		N/A
	- Current (maximum continuous) (a.c. A)		N/A
	- Current (inrush) (a.c. A, peak and duration)		N/A
	- Frequency (nominal or range) (Hz)		N/A
	d.c input (other than PV) quantities:		N/A
	- Voltage (nominal or range) (d.c. V)		N/A
	- Nominal battery voltage (d.c. V)		N/A
	- Current (maximum continuous) (d.c. A)		N/A
	d.c. output quantities:		N/A
	- Voltage (nominal or range) (d.c. V)		N/A
	- Nominal battery voltage (d.c. V)		N/A
	- Current (maximum continuous) (d.c. A)		N/A
	Protective class (I or II or III)		P
	Ingress protection (IP) rating per part 1		P
5.3.2.2	Grid-interactive inverter setpoints		P
	For a grid-interactive unit with field adjustable trip points, trip times, or reconnect times, the presence of such controls, the means for adjustment, the factory default values, and the limits of the ranges of adjustability shall be provided in the documentation for the PCE or in other format such as on a website. Provided solution:		P
	The setting of field adjustable setpoints shall be accessible from the PCE		P
5.3.2.3	Transformers and isolation		N/A
	whether an internal isolation transformer is provided, and if so, what level of insulation (functional, basic, reinforced, or double) is provided by that transformer. The instructions shall also indicate what the resulting installation requirements are regarding such things as earthing or not earthing the array, providing external residual current detection devices, etc.		N/A
	An inverter shall be provided with information to the installer regarding:		-
	- providing of internal isolation transformer		N/A
	- the level of insulation (functional, basic, reinforced, or double)		N/A
	The instructions shall also indicate what the resulting installation requirements are regarding:		-
	- earthing or not earthing the array		N/A
	- providing external residual current detection devices		N/A
	- requiring an external isolation transformer,		N/A
5.3.2.4	Transformers required but not provided		N/A
	An inverter that requires an external isolation transformer not provided with the unit, shall be provided with instructions that specify, and for the external isolation transformer with which it is intended to be used:		N/A
	- the configuration type		N/A
	- electrical ratings		N/A
	- environmental ratings		N/A
5.3.2.5	PV modules for non-isolated inverters		P
	Non-isolated inverters shall be provided with installation instructions that require PV modules that have an IEC 61730 Class A rating		P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	If the maximum AC mains operating voltage is higher than the PV array maximum system voltage then the instructions shall require PV modules that have a maximum system voltage rating based upon the AC mains voltage.		N/A
5.3.2.6	Non-sinusoidal output waveform information	Grid-connection inverter.	N/A
	The instruction manual for a stand-alone inverter not complying with 4.7.5.2 shall include a warning that:		N/A
	- the waveform is not sinusoidal,		N/A
	- some loads may experience increased heating,		N/A
	- the user should consult the manufacturers of the intended load equipment before operating that load with the inverter		N/A
	The inverter manufacturer shall provide information regarding:		-
	- what types of loads may experience increased heating		N/A
	- recommendations for maximum operating times with such loads		N/A
	The inverter manufacturer shall specify for the waveforms as determined by the testing in 4.7.5.3.2 through 4.7.5.3.4.:		-
	- THD		N/A
	- slope		N/A
	- peak voltage		N/A
5.3.2.7	Systems located in closed electrical operating areas	Not specified to be located in closed electrical operating area.	N/A
	Where required by 4.8.3.6, an inverter not provided with full protection against shock hazard on the PV array shall be provided with installation instructions:		N/A
	- requiring that the inverter and the array must be installed in closed electrical operating areas		N/A
	- indicating which forms of shock hazard protection are and are not provided integral to the inverter (for example the RCD, isolation transformer complying with the 30 mA touch current limit, or residual current monitoring for sudden changes)		N/A
5.3.2.8	Stand-alone inverter output circuit bonding	Grid-connection inverter.	N/A
	Where required by 7.3.10, the documentation for an inverter shall include the following:		N/A
	- if output circuit bonding is required but is not provided integral to the inverter, the required means shall be described in the installation instructions, including which conductor is to be bonded and the required current carrying capability or cross-section of the bonding means;		N/A
	- if the output circuit is intended to be floating, the documentation for the inverter shall indicate that the output is floating.		N/A
5.3.2.9	Protection by application of RCD's	Integrated RCM provided in inverter.	N/A
	Where the requirement for additional protection in 4.8.3.1 is met by requiring an RCD that is not provided integral to the inverter, as allowed by 4.8.3.4, the installation instructions shall state the need for the RCD,.		N/A

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	and shall specify its rating, type, and required circuit location		N/A
5.3.2.10	Remote indication of faults		P
	The installation instructions shall include an explanation of how to properly make connections to (where applicable), and use, the electrical or electronic fault indication required by 13.9.		P
5.3.2.11	External array insulation resistance measurement and response		N/A
	The installation instructions for an inverter for use with ungrounded arrays that does not incorporate all the aspects of the insulation resistance measurement and response requirements in 4.8.2.1, must include:		N/A
	- for isolated inverters: an explanation of what aspects of array insulation resistance measurement and response are not provided, and		N/A
	- an instruction to consult local regulations to determine if any additional functions are required or not;		N/A
	- for non-isolated inverters: an explanation of what external equipment must be provided in the system, and		N/A
	- what the setpoints and response implemented by that equipment must be, and:		N/A
	- how that equipment is to be interfaced with the rest of the system.		N/A
5.3.2.12	Array functional grounding information		N/A
	Where approach a) of 4.8.2.2 is used, the installation instructions for the inverter shall include all of the following:		N/A
	a) the value of the total resistance between the PV circuit and ground integral to the inverter		N/A
	b) the minimum array insulation resistance to ground that system designer or installer must meet when selecting the PV panel and system design, based on the minimum value that the design of the PV functional grounding in the inverter was based on		N/A
	c) the minimum value of the total resistance $R = V_{MAX} PV/30 \text{ mA}$ that the system must meet, with an explanation of how to calculate the total		N/A
	d) a warning that there is a risk of shock hazard if the total minimum resistance requirement is not met.		N/A
5.3.2.13	Stand-alone inverters for dedicated loads	Grid-connection inverter.	N/A
	Where the approach of 4.7.5.5 is used, the installation instructions for the inverter shall include a warning that the inverter is only to be used with the dedicated load for which it was evaluated, and shall specify the dedicated load.		N/A
5.3.2.14	Identification of firmware version(s)	See report BL-SZ1930601-B01.	P
	An inverter utilizing firmware for any protective functions shall provide means to identify the firmware version.		P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	This can be a marking, but the information can also be provided by a display panel, communications port or any other type of user interface.....		P
7	PROTECTION AGAINST ELECTRIC SHOCK AND ENERGY HAZARDS		P
7.3	Protection against electric shock		P
7.3.10	Additional requirements for stand-alone inverters		N/A
	One circuit conductor bonded to earth to create a grounded conductor and an earthed system.		N/A
	The means used to bond the grounded conductor to protective earth provided within the inverter or as part of the installation		N/A
	If not provided integral to the inverter, the required means shall be described in the installation instructions as per 5.3.2.8.		N/A
	The means used to bond the grounded conductor to protective earth shall comply with the requirements for protective bonding in Part 1,		N/A
	If the bond can only ever carry fault currents in stand-alone mode, the maximum current for the bond is determined by the inverter maximum output fault current.		N/A
	Output circuit bonding arrangements shall ensure that in any mode of operation, the system only has the grounded circuit conductor bonded to earth in one place at a time..		N/A
	Switching arrangements may be used, in which case the switching device used is to be subjected to the bond impedance test along with the rest of the bonding path		N/A
	Inverters intended to have a circuit conductor bonded to earth shall not impose any normal current on the bond except for leakage current.		N/A
	Outputs that are intentionally floating with no circuit conductor bonded to ground, must not have any voltages with respect to ground that are a shock hazard in accordance with Clause 7 of Parts 1 and 2.		N/A
	The documentation for the inverter shall indicate that the output is floating as per 5.3.2.8.		N/A
7.3.11	Functionally grounded arrays		N/A
	All PV conductors in a functionally grounded array shall be treated as being live parts with respect to protection against electric shock.		N/A
9	PROTECTION AGAINST FIRE HAZARDS		P
9.3	Short-circuit and overcurrent protection		P
9.3.4	Inverter backfeed current onto the array		P
	The backfeed current testing and documentation requirements in Part 1 apply, including but not limited to the following.		P
	Inverter backfeed current onto the PV array maximum value.....		P
	This inverter backfeed current value shall be provided in the installation instructions regardless of the value of the current, in accordance with Table 33.		P
13	PHYSICAL REQUIREMENTS		P
13.9	Fault indication		P
	Where this Part 2 requires the inverter to indicate a fault, both of the following shall be provided:		P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict
	a) a visible or audible indication, integral to the inverter, and detectable from outside the inverter, and	LCD panel is available for fault indication.	P
	b) an electrical or electronic indication that can be remotely accessed and used.	RS485 port are available for remoting communication	P
	The installation instructions shall include information regarding how to properly make connections (where applicable) and use the electrical or electronic means in b) above, in accordance with 5.3.2.10.		P

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.4.4	TABLE: Single fault condition to be applied			P
	Ambient temperature (°C)	25°C, if not stated otherwise		—
	Power source for EUT: Manufacturer, model/type, output rating	DC Source: Chroma, 62150H-1000S, 15kW. AC Source: Kewell, KACM-75-33, 75KVA.		—

4.4.4.15.1 Fault-tolerance of residual current monitoring						
Component No.	Fault	Supply voltage (V)	Test time	Fuse #	Fuse current (A)	Observation
Residual Current monitoring unit	Loss / failure (RC62 S-C)	DC 500	10 min.	--	--	PCE didn't start to work. Relay opened. SD, DG, RO, NCD, NH, PEST.
Residual Current monitoring unit	Loss / failure (CC76 S-C)	DC 500	10 min.	--	--	PCE didn't start to work. Relay opened. SD, DG, RO, NCD, NH, PEST.
Check that the residual current monitoring operates properly						RCMU operates properly.

Legend			
FID	Fault Indication	MT	Max. Temperature
SD	PCE Shut Down:	DG	Disconnection To Grid
RO	Recovered to Operate after removing the single fault setting	NCD	No Comp. or parts Damaged
NH	No Hazards occurred	PEST	Pass the Electric Strength Test.
BI	Basic insulation	SI	Supplementary insulation
DI	Double insulation	RI	Reinforced insulation
FI	Functional insulation	o-l	over-load.
s-c	short-circuited	o-c	open-circuited

Supplementary information:
The electric strength test performed after fault condition test and see appended table 7.5.2 of Part1 for detailed test conditions.

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.4.4	TABLE: Single fault condition to be applied		P
	Ambient temperature (°C)	25°C, if not stated otherwise	—
	Power source for EUT: Manufacturer, model/type, output rating	DC Source: Chroma, 62150H-1000S, 15kW. AC Source: Kewell, KACM-75-33, 75KVA.	—

4.4.4.15.2 Fault-tolerance of automatic disconnecting means						
Component No.	Fault	Supply voltage (V)	Test time	Fuse #	Fuse current (A)	Observation
RYP3 Pin3-4	S-C	PV: 500Vdc AC output: 230Vac	5min	--	--	PCE didn't start to work. Relay opened. SD, DG, RO, NCD, NH, PEST.
RYP2 Pin3-4	S-C	PV: 500Vdc AC output: 230Vac	5min	--	--	PCE didn't start to work. Relay opened. SD, DG, RO, NCD, NH, PEST.
RYP4 Pin3-4	S-C	PV: 500Vdc AC output: 230Vac	5min	--	--	PCE didn't start to work. Relay opened. SD, DG, RO, NCD, NH, PEST.
RYP5 Pin3-4	S-C	PV: 500Vdc AC output: 230Vac	5min	--	--	PCE didn't start to work. Relay opened. SD, DG, RO, NCD, NH, PEST.
Check that the relays fulfil the basic insulation or simple separation based on the PV circuit working voltage.						Relays fulfil the basic insulation or simple separation.
Each active phase can be switched. (L and N)						All pole disconnection.

Legend

FID	Fault Indication	MT	Max. Temperature
SD	PCE Shut Down:	DG	Disconnection To Grid
RO	Recovered to Operate after removing the single fault setting	NCD	No Comp. or parts Damaged
NH	No Hazards occurred	PEST	Pass the Electric Strength Test.
BI	Basic insulation	SI	Supplementary insulation
DI	Double insulation	RI	Reinforced insulation
FI	Functional insulation	o-l	over-load.
s-c	short-circuited	o-c	open-circuited

Supplementary information:
 The electric strength test performed after fault condition test and see appended table 7.5.2 of Part1 for detailed test conditions.

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.4.4.17	Cooling system failure – Blanketing test		P
	Test voltage (Vdc)..... :	300	—
	Test current (Idc)	11.2	—
	Test voltage (Vac)..... :	231.1	—
	Test current (Iac)	14.2	—
	t _{amb1} (°C)	See below.	—
	t _{amb2} (°C)	See below.	—
maximum temperature T of part/at::		T (°C)	T_{max} (°C)
	1. Ambient	25	-
	2. Enclosure outside near panel (non-metallic)	81.3	-
	3. Enclosure outside near inverter inductor (metallic)	86.7	-
	4. Mount surface	88.1	-

Supplementary information:

The inverter was operated at full power at 25°C.

The test was stopped when the over temperature protection device operated and no external surfaces of the inverter were at maximum temperature exceeding 90°C.

4.7.4	TABLE: Steady state Inverter AC output voltage and frequency		N/A
	Nominal DC input (V)	--	
	Nominal output AC voltage (V) :		
AC output U (V)	Frequency (Hz)	Condition/status	Comments
--	--	Without load	--
--	--	Resistive load application	--
--	--	Resistive load removal	--

Supplementary information:

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.8.2	TABLE: Array insulation resistance detection for inverters for ungrounded and functionally grounded arrays	P
-------	--	---

4.8.2.1	Array insulation resistance detection for inverters for ungrounded arrays	P
---------	---	---

DC Voltage below minimum operating voltage (V)	DC Voltage for inverter begin operation (V)	Resistance between ground and PV input terminal (Ω)	Required Insulation resistance $R = (V_{MAX PV} / 30mA)$ (Ω)	Identification
DC+				
50	300	I.F.	1.0MΩ	I.F.: Isolation Failure N.O.: Normal Operation
50	300	I.F.	1.0MΩ	
50	300	I.F.	1.0MΩ	
50	300	I.F.	1.0MΩ	
50	300	N.O.	1.1MΩ	
50	300	N.O.	1.1MΩ	
DC-				
50	300	I.F.	1.0MΩ	I.F.: Isolation Failure N.O.: Normal Operation
50	300	I.F.	1.0MΩ	
50	300	I.F.	1.0MΩ	
50	300	I.F.	1.0MΩ	
50	300	N.O.	1.1MΩ	
50	300	N.O.	1.1MΩ	

Note:

For isolated inverters, shall indicate a fault in accordance with 13.9 (operation is allowed); the fault indication shall be maintained until the array insulation resistance has recovered to a value higher than the limit above

For non-isolated inverters, or inverters with isolation not complying with the leakage current limits in the minimum inverter isolation requirements in Table 30, shall indicate a fault in accordance with 13.9, and shall not connect to the mains; the inverter may continue to make the measurement, may stop indicating a fault and may connect to the mains if the array insulation resistance has recovered to a value higher than the limit above.

It is not required to test all PV input terminals if analysis of the design indicates that one or more terminals can be expected to have the same result, for example where multiple PV string inputs are in parallel.

Supplementary information:

- 1) I.F. (FID: Isolation Failure)
- 2) Array Insulation Resistance Threshold Value $R = 18.3 [kΩ]$ (should be larger than $R=V_{MAX PV} / 30mA$) Ω .
- 3)Setting isolation Failure Value 1.05MΩ

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.8.3.2	TABLE: 30mA touch current type test for isolated inverters		N/A
Condition	Current (mA)	Limit (30mA)	
DC+ to PE	--	--	
DC- to PE	--	--	
Supplementary information: Non-isolated type inverter.			

4.8.3.3	TABLE: Fire hazard residual current type test for isolated inverters		N/A
Condition	Current (mA)	Limit (300mA or 10mA per kVA)	
DC+ to PE	--	--	
DC- to PE	--	--	
Supplementary information: Non-isolated type inverter.			

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.8.3.5	TABLE: Protection by residual current monitoring		P
Test conditions:		Output power (kVA) : 500Vdc Input voltage (V_{DC}): 3.3kW Frequency (Hz) 50Hz Output AC Voltage (V_{AC}): 230Vac	
4.8.3.5.2	Test for detection of excessive continuous residual current		P
Fault Current (mA)		Disconnection time (ms)	
Measured Fault Current	Limit 300mA for output power ≤ 30 kVA 10mA per kVA for output power > 30 kVA	Measured Disconnection time	Limit
+ PV to N:			
251.0	330	210.5	300
250.7	330	219.0	300
252.0	330	207.0	300
251.0	330	213.0	300
250.7	330	209.0	300
- PV to N:			
254.3	330	224.5	300
245.4	330	204.0	300
242.0	330	227.0	300
247.6	330	219.5	300
247.3	330	214.5	300
Note:			
<ul style="list-style-type: none"> – maximum 300mA for inverters with continuous output power rating ≤30 kVA; – maximum 10mA per kVA of rated continuous output power for inverters with continuous output power rating > 30 kVA. <p>This test shall be repeated 5 times, and for all 5 tests the time to disconnect shall not exceed 0,3s. The test is repeated for each PV input terminal. It is not required to test all PV input terminals if analysis of the design indicates that one or more terminals can be expected to have the same result, for example where multiple PV string inputs are in parallel.</p>			
Supplementary information:			

IEC 62109-2			
Clause	Requirement + Test	Result - Remark	Verdict

4.8.3.5.3 TABLE: Test for detection of sudden changes in residual current			
+PV to N			
Limit (mA)	U_N		Limit (ms)
	Disconnection time (ms)		
30	199.5		300
30	200.0		300
30	198.0		300
30	216.5		300
30	219.5		300
60	121.0		150
60	123.5		150
60	118.0		150
60	127.0		150
60	107.5		150
150	25.0		40
150	35.0		40
150	22.8		40
150	31.0		40
150	24.2		40
-PV to N			
Limit (mA)	U_N		Limit (ms)
	Disconnection time (ms)		
30	193.5		300
30	218.5		300
30	217.5		300
30	222.0		300
30	218.0		300
60	109.5		150
60	111.0		150
60	123.0		150
60	119.0		150
60	121.5		150
150	16.0		40
150	33.0		40
150	28.2		40
150	19.2		40
150	20.2		40

Note:

The capacitive current is raised until disconnection.

Test condition: $I_c + 30/60/150mA \leq I_{cmax}$. R₁ is set that 30/60/150mA Flow and switch S is closed.

Supplementary information:

100% output power and V_{mppmax} input voltage

List of test equipment used:

No.	Equipment name	Manufacture	Serial No.	Calibration Data	Usage
1	Solar IV simulator	Kewell	BZ-EP-L002	--	√
2	Solar IV simulator	Chroma	BZ-EP-L039	--	√
3	Programmable ac load	QunLing	BZ-EP-L003	--	√
4	Power analyzer	HIOKI	BZ-EP-L005	2020/02/26	√
5	Oscilloscope	Tektronix	BZ-EP-L016	2020/02/26	√
6	Heating Recoder	Agilent	BZ-EP-L021	2019/11/01	√
7	Hi-Pot & IR tester	Chroma	BZ-EP-L022	2019/10/31	√
8	Noise meter	TES	BZ-EP-L023	2020/3/10	√
9	Spring Hammer	BLS	BZ-EP-L034	2020/3/17	√
10	Digital Caliper	CHUANLIANG	BZ-SFT-L003	2019/10/31	√
11	Testing Finger B	AODESAI	BZ-SFT-L011	2019/11/1	√
12	DC Electronic Load	Itech	BZ-SFT-L028	2019/10/31	√
13	Pull and push	HANDPI	BZ-SFT-L045	2019/10/31	√
14	Electronic Scale	/	BZ-SFT-L087	2020/2/25	√
15	Thermostat	Hading	BZ-KKX-L003	2019/10/31	√
16	Sand and dust chamber	Gongwen	BZ-KKX-L010	2019/6/3	√
17	Strong flushing test device	Gongwen	BZ-KKX-L009	2019/10/31	√
18	Surge generator	/	BZ-EMC-L015	2019/6/12	√
19	Stop watch	TF	BZ-SFT-L068	2019/06/19	√
20	Ground Resistance Tester	AINUO	BZ-SFT-L033	2019.10.31	√
21	Leakage current test network	Anbiao	BZ-SFT-L111	2020/03/02	√
22	Multimeter	FULKE	BZ-EP-L033	2020/02/25	

- End of test report -